



Section 25. Device Configuration

HIGHLIGHTS

This section of the manual contains the following major topics:

25.1	Introduction	25-2
25.2	Device Configuration Registers	25-3
25.3	Configuration Bit Descriptions.....	25-11
25.4	Device Identification Registers.....	25-12
25.5	Registers Associated with Device Configuration	25-13
25.6	Related Application Notes.....	25-15
25.7	Revision History	25-16

25.1 INTRODUCTION

The Device Configuration registers allow each user to customize certain aspects of the device to fit the needs of the application. Device configuration registers are nonvolatile locations in program memory that hold settings for the dsPIC device during power-down. The configuration registers hold global set-up information for the device, such as the oscillator source, Watchdog Timer mode, code protection settings and others.

The device configuration registers are mapped in program memory locations, starting at address 0xF80000, and are accessible during normal device operation. This region is also referred to as “configuration space.”

The configuration bits can be programmed (read as ‘0’) or left unprogrammed (read as ‘1’) to select various device configurations.

25.2 DEVICE CONFIGURATION REGISTERS

Each device configuration register is a 24-bit register. However, only the lower 16 bits of each register hold configuration data. Seven device configuration registers are available to user software:

- FBS: Boot Code Segment Configuration Register
- FSS: Secure Code Segment Configuration Register
- FGS: General Code Segment Configuration Register
- FOSCSEL: Oscillator Source Selection Register
- FOSC: Oscillator Configuration Register
- FWDT: Watchdog Timer Configuration Register
- FPOR: POR Configuration Register

The device configuration registers can be programmed using Run-Time Self-Programming (RTSP), In-Circuit Serial Programming™ (ICSP™) or a device programmer.

Note: Some configuration registers and bits may not be present on all dsPIC33F devices. Consult the specific device data sheet for more information.

dsPIC33F Family Reference Manual

Register 25-1: FBS: Boot Code Segment Configuration Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23						bit 16	

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15						bit 8	

R/P	R/P	U	U	R/P	R/P	R/P	R/P
RBS<1:0>		—	—	BSS<2:0>		BWRP	
bit 7						bit 0	

Legend:

R = Readable bit P = Programmable bit U = Unimplemented bit, read as '0'
 -n = Value at POR '1' = Bit is set '0' = Bit is cleared x = Bit is unknown

- bit 23-8 **Unimplemented:** Read as '0'
- bit 7-6 **RBS<1:0>:** Boot Segment RAM Code Protection bits
 - 11 = No Boot RAM defined
 - 10 = Boot RAM is 128 bytes
 - 01 = Boot RAM is 256 bytes
 - 00 = Boot RAM is 1024 bytes
- bit 5-4 **Unimplemented:** Read as '0'
- bit 3-1 **BSS<2:0>:** Boot Segment Program Flash Code Protection Size bits (see the specific device data sheet for more information)
- bit 0 **BWRP:** Boot Segment Program Flash Write Protection bit
 - 1 = Boot segment may be written
 - 0 = Boot segment is write-protected

Section 25. Device Configuration

Register 25-2: FSS: Secure Code Segment Configuration Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23						bit 16	

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15						bit 8	

R/P	R/P	U	U	R/P	R/P	R/P	R/P
RSS<1:0>		—	—	SSS<2:0>		SWRP	
bit 7						bit 0	

Legend:

R = Readable bit	P = Programmable bit	U = Unimplemented bit, read as '0'	
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared	x = Bit is unknown

- bit 23-8 **Unimplemented:** Read as '0'
- bit 7-6 **RSS<1:0>:** Secure Segment RAM Code Protection bits
 - 11 = No Secure RAM defined
 - 10 = Secure RAM is 256 bytes, less BS RAM
 - 01 = Secure RAM is 2048 bytes, less BS RAM
 - 00 = Secure RAM is 4096 bytes, less BS RAM
- bit 5-4 **Unimplemented:** Read as '0'
- bit 3-1 **SSS<2:0>:** Secure Segment Program Flash Code Protection Size bits (see the specific device data sheet for more information)
- bit 0 **SWRP:** Secure Segment Program Flash Write Protection bit
 - 1 = Secure segment may be written
 - 0 = Secure segment is write-protected

dsPIC33F Family Reference Manual

Register 25-3: FGS: General Code Segment Configuration Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23						bit 16	

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15						bit 8	

U	U	U	U	U	R/P	R/P	R/P
—	—	—	—	—	GSS<1:0>		GWRP
bit 7						bit 0	

Legend:

R = Readable bit P = Programmable bit U = Unimplemented bit, read as '0'
 -n = Value at POR '1' = Bit is set '0' = Bit is cleared x = Bit is unknown

- bit 23-3 **Unimplemented:** Read as '0'
- bit 2-1 **GSS<1:0>:** General Segment Code-Protect bit
 - 11 = User program memory is not code-protected
 - 10 = Standard security
 - 0x = High security
- bit 0 **GWRP:** General Segment Program Flash Write Protection bit
 - 1 = General segment may be written
 - 0 = General segment is write-protected

Section 25. Device Configuration

Register 25-4: FOSCSEL: Oscillator Source Selection Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23						bit 16	

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15						bit 8	

R/P	U	R/P	U	U	R/P	R/P	R/P
IESO	—	TEMP	—	—	FNOSC<2:0>		
bit 7						bit 0	

Legend:

R = Readable bit P = Programmable bit U = Unimplemented bit, read as '0'
 -n = Value at POR '1' = Bit is set '0' = Bit is cleared x = Bit is unknown

- bit 23-8 **Unimplemented:** Read as '0'
- bit 7 **IESO:** Two-speed Oscillator Start-up Enable bit
 1 = Start device with FRC, then automatically switch to the user-selected oscillator source when ready
 0 = Start device with the user-selected oscillator source
- bit 6 **Unimplemented:** Read as '0'
- bit 5 **TEMP:** Temperature Protection Enable bit
 1 = Temperature protection disabled
 0 = Temperature protection enabled
- bit 4-3 **Unimplemented:** Read as '0'
- bit 2-0 **FNOSC<2:0>:** Initial Oscillator Source Selection bits
 111 = Internal Fast RC (FRC) oscillator with postscaler
 110 = Internal FRC oscillator with divide-by-16
 101 = LPRC oscillator
 100 = Secondary (LP) oscillator
 011 = Primary (XT, HS, EC) oscillator with PLL
 010 = Primary (XT, HS, EC) oscillator
 001 = Internal FRC oscillator with PLL
 000 = FRC oscillator

dsPIC33F Family Reference Manual

Register 25-5: FOSC: Oscillator Configuration Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23						bit 16	

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15						bit 8	

R/P	R/P	R/P	U	U	R/P	R/P	R/P
FCKSM<1:0>		IOL1WAY	—	—	OSCIOFNC	POSCMD<1:0>	
bit 7						bit 0	

Legend:

R = Readable bit	P = Programmable bit	U = Unimplemented bit, read as '0'
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared
		x = Bit is unknown

- bit 23-8 **Unimplemented:** Read as '0'
- bit 7-6 **FCKSM<1:0>:** Clock Switching Mode bits
 - 1x = Clock switching is disabled; Fail-Safe Clock Monitor is disabled
 - 01 = Clock switching is enabled; Fail-Safe Clock Monitor is disabled
 - 00 = Clock switching is enabled; Fail-Safe Clock Monitor is enabled
- bit 5 **IOL1WAY:** Peripheral Pin Select Configuration bit
 - 1 = Allow only one reconfiguration
 - 0 = Allow multiple reconfigurations
- bit 4-3 **Unimplemented:** Read as '0'
- bit 2 **OSCIOFNC:** OSC2 Pin Function bit (except in XT and HS modes)
 - 1 = OSC2 is clock output
 - 0 = OSC2 is general-purpose digital I/O pin
- bit 1-0 **POSCMD<1:0>:** Primary Oscillator Mode Select bits
 - 11 = Primary oscillator disabled
 - 10 = HS Crystal Oscillator mode
 - 01 = XT Crystal Oscillator mode
 - 00 = EC (External Clock) mode

Section 25. Device Configuration

Register 25-6: FWDT: Watchdog Timer Configuration Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23						bit 16	

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15						bit 8	

R/P	R/P	R/P	U	U	R/P	R/P	R/P
FWDTEN	WINDIS	—	WDTPRE		WDTPOST<3:0>		
bit 7						bit 0	

Legend:

R = Readable bit	P = Programmable bit	U = Unimplemented bit, read as '0'
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared x = Bit is unknown

- bit 23-8 **Unimplemented:** Read as '0'
- bit 7 **FWDTEN:** Watchdog Timer Enable Mode bit
 - 1 = Watchdog Timer always enabled (LPRC oscillator cannot be disabled. Clearing the SWDTEN bit in the RCON register will have no effect.)
 - 0 = Watchdog Timer enabled/disabled by user software (LPRC can be disabled by clearing the SWDTEN bit in the RCON register)
- bit 6 **WINDIS:** Watchdog Timer Window Enable bit
 - 1 = Watchdog Timer in Non-Window mode
 - 0 = Watchdog Timer in Window mode
- bit 5 **Unimplemented:** Read as '0'
- bit 4 **WDTPRE:** Watchdog Timer Prescaler bit
 - 1 = 1:128
 - 0 = 1:32
- bit 3-0 **WDTPOST<3:0>:** Watchdog Timer Postscaler bits
 - 1111 = 1:32,768
 - 1110 = 1:15,384
 - .
 - .
 - .
 - 0001 = 1:2
 - 0000 = 1:1

dsPIC33F Family Reference Manual

Register 25-7: FPOR: POR Configuration Register

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 23						bit 16	

U	U	U	U	U	U	U	U
—	—	—	—	—	—	—	—
bit 15						bit 8	

R/P	R/P	R/P	U	U	R/P	R/P	R/P
PWMPIN	HPOL	LPOL	ALT2C	—	FPWRT<2:0>		
bit 7						bit 0	

Legend:

R = Readable bit	P = Programmable bit	U = Unimplemented bit, read as '0'
-n = Value at POR	'1' = Bit is set	'0' = Bit is cleared
		x = Bit is unknown

- bit 23-8 **Unimplemented:** Read as '0'
- bit 7 **PWMPIN:** Motor Control PWM Module Pin Mode bit
 - 1 = PWM module pins controlled by PORT register at device Reset (tri-stated)
 - 0 = PWM module pins controlled by PWM module at device Reset (configured as output pins)
- bit 6 **HPOL:** Motor Control PWM High-Side Polarity bit
 - 1 = PWM module high-side output pins have active-high output polarity
 - 0 = PWM module high-side output pins have active-low output polarity
- bit 5 **LPOL:** Motor Control PWM Low-Side Polarity bit
 - 1 = PWM module low-side output pins have active-high output polarity
 - 0 = PWM module low-side output pins have active-low output polarity
- bit 4 **ALT2C:** Alternate I²C™ Pins bit
 - 1 = I²C mapped to SDA1/SCL1 pins
 - 0 = I²C mapped to ASDA1/ASCL1 pins
- bit 3 **Unimplemented:** Read as '0'
- bit 2-0 **FPWRT<2:0>:** Power-on Reset Timer Value Select bits
 - 111 = PWRT = 128 ms
 - 110 = PWRT = 64 ms
 - 101 = PWRT = 32 ms
 - 100 = PWRT = 16 ms
 - 011 = PWRT = 8 ms
 - 010 = PWRT = 4 ms
 - 001 = PWRT = 2 ms
 - 000 = PWRT = Disabled

25.3 CONFIGURATION BIT DESCRIPTIONS

This section provides functional information for each of the device configuration bits.

25.3.1 Code Protection and CodeGuard™ Security

The dsPIC33F product families offer advanced security which protects the Intellectual Property that users invest in collaborative system designs. CodeGuard™ Security enables multiple parties to securely share resources (memory, interrupts and peripherals) on a single chip with assurance that their Intellectual Property rights are not at risk.

The code protection features are controlled by the configuration registers (FBS, FSS and FGS) and vary from one dsPIC33F device to another. For further information, consult the device data sheet and refer to **Section 23. “Security”** in this reference manual.

25.3.2 Oscillator Configuration Bits

The dsPIC33F clock selection, switching and configuration settings are controlled by the Oscillator Source Selection (FOSCSEL) and Oscillator Configuration (FOSC) registers. See **Section 7. “Oscillator”** for more information.

25.3.3 POR Configuration Bits

The POR configuration bits, found in the FPOR configuration register, are used to set the Power-up Timer delay time. For more information on these configuration bits, please refer to **Section 8. “Reset”**.

25.3.4 Motor Control PWM Module Configuration Bits

The Motor Control PWM module configuration bits are located in the FPOR configuration register and are present only on devices that have the PWM module. The configuration bits associated with the PWM module have two functions:

- Select the state of the PWM pins at a device Reset (high-Z or output).
- Select the active signal polarity for the PWM pins. The polarity for the high-side and low-side PWM pins can be selected independently.

For more information on these configuration bits, please refer to **Section 14. “Motor Control PWM”**.

25.3.5 Watchdog Timer Configuration Bits

The dsPIC33F Watchdog Timer can be enabled and configured using the Watchdog Timer Configuration Register (FWDT). **Section 9. “WatchDog Timer and Power Savings Modes”** provides more information on these configuration bits.

25.4 DEVICE IDENTIFICATION REGISTERS

The dsPIC33F devices have two sets of registers located in configuration space that provide identification information.

25.4.1 Device ID (DEVID) Registers

Configuration memory space locations 0xFF0000 and 0xFF0002 are used to store a read-only Device ID number that is set when the device is manufactured. This number identifies the dsPIC33F device type and the silicon revision.

The Device ID registers can be read using table read instructions.

25.4.2 Unit ID Field

The Unit ID field is located at configuration memory space locations 0xF80010 through 0xf80016. This field consists of four configuration registers (FUID0-FUID3) and can be programmed with unique device information.

25.5 REGISTERS ASSOCIATED WITH DEVICE CONFIGURATION

A summary of the registers associated with dsPIC33F device configuration is provided in Table 25-1.

Table 25-1: Device Configuration Register Map

Name	Addr.	Bits 23 - 8 (Not used for device configuration)	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
FBS	0xF80000	—	RBS<1:0>		—	—	BSS<2:0>		BWRP	
FSS	0xF80002	—	RSS<1:0>		—	—	SSS<2:0>		SWRP	
FGS	0xF80004	—	—	—	—	—	GSS<1:0>		GWRP	
FOSCSEL	0xF80006	—	IESO	—	TEMP	—	—	FNOSC<2:0>		
FOSC	0xF80008	—	FCKSM<1:0>		IOL1WAY	—	—	OSCIOFNC	POSCMD<1:0>	
FWDT	0xF8000A	—	FWDTEN	WINDIS	—	WDTPRE	WDTPOST<3:0>			
FPOR	0xF8000C	—	PWMPIN	HPOL	LPOL	ALT12C	—	FPWRT<2:0>		
FUID0	0xF80010	—	User Unit ID Byte 0							
FUID1	0xF80012	—	User Unit ID Byte 1							
FUID2	0xF80014	—	User Unit ID Byte 2							
FUID3	0xF80016	—	User Unit ID Byte 3							

Legend: — = unimplemented, read as 0. Reset values are shown in hexadecimal.

Note: Some configuration registers and bits may not be present on all dsPIC33F devices. Consult the specific device data sheet for more information.

25.6 RELATED APPLICATION NOTES

This section lists application notes that are related to this section of the manual. These application notes may not be written specifically for the dsPIC33F product family, but the concepts are pertinent and could be used with modification and possible limitations. The current application notes related to the Device Configuration registers include the following:

Title	Application Note #
No related application notes at this time.	

Note: Please visit the Microchip web site (www.microchip.com) for additional Application Notes and code examples for the dsPIC33F family of devices.

25.7 REVISION HISTORY

Revision A (February 2007)

This is the initial release of this section.

Revision B (February 2007)

Minor edits throughout document.